

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 870 MHz Signal Directors for:

Antec Style Jumpers, Splitters and D/C's Series Manufactured By Mainline

Part Number	Path	Insertion Loss @ MHz					Port Routing	
		5	54	550	750	870	MB	LE
MANTE-SPL	Split	3.3	3.3	3.6	4.1	4.5	2,4	2,3
MANTDC-J	Jumper	0.0	0.0	0.0	0.0	0.0	2	2
MANTDC-JI	Jumper	0.0	0.0	0.0	0.0	0.0	4	3
MANTDC-08	Tap	9.3	8.9	8.3	8.2	8.1	2	3
	Thru	1.6	1.3	1.5	1.9	2.2	4	2
MANTDC-08I	Tap	9.3	8.9	8.3	8.2	8.1	4	2
	Thru	1.6	1.3	1.5	1.9	2.2	2	3
MANTDC-12	Tap	13.2	12.5	12.3	12.4	12.5	2	3
	Thru	1.7	1.0	1.2	1.4	1.7	4	2
MANTDC-12I	Tap	13.2	12.5	12.3	12.4	12.5	4	2
	Thru	1.7	1.0	1.2	1.4	1.7	2	3

Return Loss I/O: **18/18 dB**

Note: Measurements on individual signal directors may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.