

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 750 MHz Forward Equalizers for:

Antec Style MEQ750/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz							Tilt (dB)
		50	150	350	450	550	650	750	
MANTE-J	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
MANTE-00	0.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	0.0
MANTE750-01	1.0	2.0	1.8	1.5	1.4	1.4	1.3	1.2	0.8
MANTE750-02	2.0	2.7	2.4	1.9	1.7	1.5	1.4	1.2	1.5
MANTE750-03	3.0	3.5	2.9	2.2	1.9	1.7	1.4	1.2	2.3
MANTE750-04	4.0	4.2	3.5	2.6	2.2	1.8	1.5	1.2	3.0
MANTE750-05	5.0	5.0	4.1	2.9	2.4	2.0	1.6	1.2	3.8
MANTE750-06	6.0	5.8	4.7	3.2	2.7	2.1	1.7	1.2	4.6
MANTE750-07	7.0	6.5	5.3	3.6	2.9	2.3	1.8	1.2	5.3
MANTE750-08	8.0	7.3	5.9	3.9	3.2	2.5	1.8	1.2	6.1
MANTE750-09	9.0	8.0	6.4	4.2	3.4	2.6	1.9	1.2	6.8
MANTE750-10	10.0	8.8	7.0	4.6	3.7	2.8	2.0	1.2	7.6
MANTE750-11	11.0	9.6	7.6	4.9	3.9	2.9	2.1	1.2	8.4
MANTE750-12	12.0	10.3	8.2	5.3	4.1	3.1	2.1	1.2	9.1
MANTE750-13	13.0	11.1	8.8	5.6	4.4	3.2	2.2	1.2	9.9
MANTE750-14	14.0	11.8	9.4	5.9	4.6	3.4	2.3	1.2	10.6
MANTE750-15	15.0	12.6	9.9	6.3	4.9	3.6	2.4	1.2	11.4
MANTE750-16	16.0	13.3	10.5	6.6	5.1	3.7	2.5	1.2	12.1
MANTE750-17	17.0	14.1	11.1	6.9	5.4	3.9	2.5	1.2	12.9
MANTE750-18	18.0	14.9	11.7	7.3	5.6	4.0	2.6	1.2	13.7

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.15 dB** cable equivalent

Note: Measurements on individual forward equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.