

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 870 MHz Forward Equalizers for:

Antec Style MEQ870/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz								Tilt (dB)
		50	150	350	450	550	650	750	870	
MANTE-J	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
MANTE-00	0.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	0.0
MANTE870-01	1.0	1.8	1.6	1.4	1.3	1.2	1.1	1.1	1.0	0.8
MANTE870-02	2.0	2.6	2.2	1.8	1.6	1.4	1.3	1.2	1.0	1.6
MANTE870-03	3.0	3.3	2.8	2.2	1.9	1.7	1.4	1.2	1.0	2.3
MANTE870-04	4.0	4.1	3.5	2.6	2.2	1.9	1.6	1.3	1.0	3.1
MANTE870-05	5.0	4.9	4.1	2.9	2.5	2.1	1.7	1.4	1.0	3.9
MANTE870-06	6.0	5.7	4.7	3.3	2.8	2.3	1.9	1.5	1.0	4.7
MANTE870-07	7.0	6.4	5.3	3.7	3.1	2.6	2.0	1.5	1.0	5.4
MANTE870-08	8.0	7.2	5.9	4.1	3.4	2.8	2.2	1.6	1.0	6.2
MANTE870-09	9.0	8.0	6.5	4.5	3.7	3.0	2.3	1.7	1.0	7.0
MANTE870-10	10.0	8.8	7.2	4.9	4.0	3.2	2.5	1.8	1.0	7.8
MANTE870-11	11.0	9.8	8.0	5.5	4.5	3.6	2.8	2.0	1.2	8.6
MANTE870-12	12.0	10.5	8.6	5.9	4.8	3.9	3.0	2.1	1.2	9.3
MANTE870-13	13.0	11.3	9.2	6.3	5.1	4.1	3.1	2.2	1.2	10.1
MANTE870-14	14.0	12.1	9.8	6.6	5.4	4.3	3.3	2.3	1.2	10.9
MANTE870-15	15.0	12.9	10.4	7.0	5.8	4.5	3.4	2.4	1.2	11.7
MANTE870-16	16.0	13.6	11.0	7.4	6.1	4.8	3.6	2.4	1.2	12.4
MANTE870-17	17.0	14.4	11.7	7.8	6.4	5.0	3.7	2.5	1.2	13.2
MANTE870-18	18.0	15.2	12.3	8.2	6.7	5.2	3.9	2.6	1.2	14.0

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.15 dB** cable equivalent

Note: Measurements on individual forward equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.