

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p><a href="http://www.main-line-inc.com">www.main-line-inc.com</a> e-mail: <a href="mailto:sales@main-line-inc.com">sales@main-line-inc.com</a> <a href="mailto:engineering@main-line-inc.com">engineering@main-line-inc.com</a></p>
--	------------------------------	--

Replacement 42 MHz Reverse Equalizers for:

### Antec Style MREQ42/\* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz		Tilt (dB)
		5	42	
MANTE-J	<b>0.0</b>	0.0	0.0	<b>0.0</b>
MANTE-00	<b>0.0</b>	1.0	1.0	<b>0.0</b>
MANTRE42-01	<b>1.0</b>	2.5	1.2	<b>1.3</b>
MANTRE42-02	<b>2.0</b>	3.0	1.2	<b>1.8</b>
MANTRE42-03	<b>3.0</b>	3.5	1.2	<b>2.3</b>
MANTRE42-04	<b>4.0</b>	4.0	1.2	<b>2.8</b>
MANTRE42-05	<b>5.0</b>	4.5	1.2	<b>3.3</b>
MANTRE42-06	<b>6.0</b>	5.0	1.2	<b>3.8</b>
MANTRE42-07	<b>7.0</b>	5.5	1.2	<b>4.3</b>
MANTRE42-08	<b>8.0</b>	6.0	1.2	<b>4.8</b>
MANTRE42-09	<b>9.0</b>	6.5	1.2	<b>5.3</b>
MANTRE42-10	<b>10.0</b>	7.0	1.2	<b>5.8</b>

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.2 dB** cable equivalent

*Note: Measurements on individual reverse equalizers may differ slightly from these values.*