



SPECIFICATION SHEET

20917 Higgins Court
Torrance, Ca. 90501

Phone: 310-357-4450

800-444-2288

Fax: 310-357-4465

www.main-line-inc.com

e-mail: sales@main-line-inc.com

engineering@main-line-inc.com

Replacement 55 MHz Reverse Equalizers for:

Antec Style MREQ55/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz		Tilt (dB)
		5	55	
<i>MANTE-J</i>	0.0	0.0	0.0	0.0
<i>MANTE-00</i>	0.0	1.0	1.0	0.0
<i>MANTRE55-01</i>	1.0	2.5	1.2	1.3
<i>MANTRE55-02</i>	2.0	3.0	1.2	1.8
<i>MANTRE55-03</i>	3.0	3.5	1.2	2.3
<i>MANTRE55-04</i>	4.0	4.0	1.2	2.8
<i>MANTRE55-05</i>	5.0	4.5	1.2	3.3
<i>MANTRE55-06</i>	6.0	5.0	1.2	3.8
<i>MANTRE55-07</i>	7.0	5.5	1.2	4.3
<i>MANTRE55-08</i>	8.0	6.0	1.2	4.8
<i>MANTRE55-09</i>	9.0	6.5	1.2	5.3
<i>MANTRE55-10</i>	10.0	7.0	1.2	5.8

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.2 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.