



# SPECIFICATION SHEET

20917 Higgins Court  
Torrance, Ca. 90501

Phone: 310-357-4450

800-444-2288

Fax: 310-357-4465

[www.main-line-inc.com](http://www.main-line-inc.com)

e-mail: [sales@main-line-inc.com](mailto:sales@main-line-inc.com)

[engineering@main-line-inc.com](mailto:engineering@main-line-inc.com)

Replacement 65 MHz Reverse Equalizers for:

## Antec Style MREQ65/\* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz		Tilt (dB)
		5	65	
<i>MANTE-J</i>	0.0	0.0	0.0	<b>0.0</b>
<i>MANTE-00</i>	0.0	1.0	1.0	<b>0.0</b>
<i>MANTRE65-01</i>	1.0	3.0	1.2	<b>1.8</b>
<i>MANTRE65-02</i>	2.0	3.5	1.2	<b>2.3</b>
<i>MANTRE65-03</i>	3.0	4.0	1.2	<b>2.8</b>
<i>MANTRE65-04</i>	4.0	4.5	1.2	<b>3.3</b>
<i>MANTRE65-05</i>	5.0	5.0	1.2	<b>3.8</b>
<i>MANTRE65-06</i>	6.0	5.5	1.2	<b>4.3</b>
<i>MANTRE65-07</i>	7.0	6.0	1.2	<b>4.8</b>
<i>MANTRE65-08</i>	8.0	6.5	1.2	<b>5.3</b>
<i>MANTRE65-09</i>	9.0	7.0	1.2	<b>5.8</b>
<i>MANTRE65-10</i>	10.0	7.5	1.2	<b>6.3</b>

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.2 dB** cable equivalent

*Note: Measurements on individual reverse equalizers may differ slightly from these values.*

\*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.