

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 42 MHz Reverse Equalizers for:

Augat Style 42/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz					Tilt (dB)
		5	15	25	30	42	
MAUGRE42-00	0.0	0.47	1.26	1.30	1.28	0.32	0.15
MAUGRE42-03	3.0	2.74	2.55	2.07	1.76	0.20	2.54
MAUGRE42-06	6.0	4.95	4.12	3.03	2.43	0.28	4.67
MAUGRE42-09	9.0	6.57	5.10	3.62	2.80	0.68	5.89
MAUGRE42-13.5	13.5	10.32	8.34	5.95	4.80	0.70	9.62
MAUGRE42-21	21.0	15.40	12.11	8.32	6.42	0.58	14.82

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.