

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 42 MHz Reverse Equalizers for:

Augat Style 42B/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz					Tilt (dB)
		5	15	25	30	42	
MAUGRE42B-00	0.0	3.02	3.16	2.85	2.63	0.58	2.44
MAUGRE42B-1.5	1.5	4.60	4.38	3.82	3.54	0.64	3.96
MAUGRE42B-03	3.0	5.82	5.28	4.36	3.90	0.82	5.00
MAUGRE42B-4.5	4.5	6.59	5.65	4.46	3.91	0.62	5.97
MAUGRE42B-06	6.0	7.04	6.02	4.58	3.85	0.71	6.33
MAUGRE42B-7.5	7.5	9.11	7.26	5.64	4.84	0.86	8.25
MAUGRE42B-09	9.0	9.58	8.02	6.26	5.27	0.50	9.08
MAUGRE42B-10.5	10.5	10.81	8.06	6.00	5.05	0.70	10.11
MAUGRE42B-12	12.0	11.36	8.48	6.05	4.92	0.52	10.84

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.