


| | | |
|--|------------------------------|--|
|  | <h2>SPECIFICATION SHEET</h2> | <p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p> |
|--|------------------------------|--|

Replacement 862 MHz Forward Equalizers for:

C-COR Style SEQ-862/* Series Manufactured By Mainline

| Part Number | Value (dB) | Insertion Loss @ MHz | | | | | | | | Tilt (dB) |
|-------------|-------------|----------------------|------|-----|-----|-----|-----|-----|-----|-------------|
| | | 54 | 200 | 400 | 500 | 600 | 700 | 800 | 862 | |
| MCCRE-00 | 0.0 | 0.0 | 0.0 | 0.0 | 0.0 | 0.0 | 0.0 | 0.0 | 0.0 | 0.0 |
| MCCRE862-02 | 2.0 | 1.9 | 1.8 | 1.5 | 1.4 | 1.3 | 1.2 | 1.1 | 1.0 | 0.9 |
| MCCRE862-03 | 3.0 | 2.9 | 2.4 | 1.7 | 1.6 | 1.5 | 1.4 | 1.2 | 1.0 | 1.9 |
| MCCRE862-04 | 4.0 | 4.0 | 3.2 | 2.2 | 1.9 | 1.6 | 1.4 | 1.2 | 1.0 | 3.0 |
| MCCRE862-05 | 5.0 | 4.8 | 3.4 | 2.5 | 2.1 | 1.7 | 1.4 | 1.2 | 1.0 | 3.8 |
| MCCRE862-06 | 6.0 | 5.9 | 4.4 | 3.0 | 2.6 | 2.1 | 1.6 | 1.2 | 1.0 | 4.9 |
| MCCRE862-07 | 7.0 | 6.9 | 5.4 | 3.7 | 3.1 | 2.5 | 1.9 | 1.4 | 1.0 | 5.9 |
| MCCRE862-08 | 8.0 | 7.8 | 5.7 | 4.0 | 3.4 | 2.7 | 2.1 | 1.4 | 1.0 | 6.8 |
| MCCRE862-09 | 9.0 | 8.8 | 6.5 | 4.4 | 3.6 | 2.8 | 2.0 | 1.4 | 1.0 | 7.8 |
| MCCRE862-10 | 10.0 | 9.6 | 7.0 | 4.8 | 3.8 | 2.9 | 2.1 | 1.4 | 1.0 | 8.6 |
| MCCRE862-11 | 11.0 | 10.8 | 8.0 | 5.4 | 4.4 | 3.5 | 2.5 | 1.6 | 1.0 | 9.8 |
| MCCRE862-12 | 12.0 | 11.6 | 8.5 | 5.8 | 4.7 | 3.7 | 2.7 | 1.7 | 1.0 | 10.6 |
| MCCRE862-13 | 13.0 | 12.8 | 9.4 | 6.3 | 5.0 | 3.9 | 2.8 | 1.7 | 1.0 | 11.8 |
| MCCRE862-14 | 14.0 | 13.6 | 10.0 | 6.5 | 5.2 | 4.0 | 2.9 | 1.8 | 1.0 | 12.6 |
| MCCRE862-15 | 15.0 | 14.5 | 10.5 | 7.0 | 5.6 | 4.2 | 3.0 | 1.8 | 1.0 | 13.5 |
| MCCRE862-16 | 16.0 | 15.3 | 11.2 | 7.6 | 6.1 | 4.7 | 3.3 | 2.0 | 1.0 | 14.3 |
| MCCRE862-17 | 17.0 | 17.5 | 12.7 | 8.5 | 6.5 | 5.1 | 3.5 | 2.0 | 1.0 | 16.5 |
| MCCRE862-18 | 18.0 | 18.4 | 13.3 | 8.7 | 6.8 | 5.2 | 3.6 | 2.0 | 1.0 | 17.4 |
| MCCRE862-19 | 19.0 | 19.5 | 14.2 | 9.0 | 7.2 | 5.7 | 3.8 | 2.0 | 1.0 | 18.5 |
| MCCRE862-20 | 20.0 | 20.3 | 14.8 | 9.6 | 7.6 | 5.8 | 3.9 | 2.0 | 1.0 | 19.3 |

Return Loss I/O: **20/18 dB**
Passband Flatness: **+/-0.30 dB** cable equivalent

Note: Measurements on individual forward equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.