

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 40 MHz Reverse Equalizers for:

General Instruments Style SEE-40/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz					Tilt (dB)
		5	15	25	30	40	
MGIRE40-00	0.0	1.85	1.84	1.80	1.71	0.48	1.37
MGIRE40-02	2.0	3.14	2.84	2.36	2.04	0.82	2.32
MGIRE40-04	4.0	4.43	3.70	2.82	2.30	0.39	4.04
MGIRE40-06	6.0	5.74	4.51	3.24	2.52	0.66	5.08
MGIRE40-07	7.0	6.03	4.90	3.54	2.84	1.12	4.91
MGIRE40-08	8.0	7.16	5.52	3.83	2.98	0.72	6.44
MGIRE40-10	10.0	8.49	6.28	4.18	3.22	0.92	7.57
MGIRE40-12	12.0	9.91	6.99	4.42	3.31	0.68	9.23

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.