

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 55 MHz Reverse Equalizers for:

General Instruments Style SEE-55/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz						Tilt (dB)
		5	15	25	30	40	55	
MGIRE55-00	0.0	2.29	2.29	2.28	2.25	2.12	0.86	1.43
MGIRE55-02	2.0	4.07	3.91	3.61	3.44	2.99	1.49	2.58
MGIRE55-04	4.0	4.60	4.03	3.40	3.08	2.25	0.20	4.40
MGIRE55-04.4	4.4	4.79	4.12	3.43	3.09	2.23	0.20	4.59
MGIRE55-06	6.0	5.89	4.93	4.00	3.59	2.66	0.50	5.39
MGIRE55-08	8.0	8.11	6.91	5.40	4.67	3.22	0.66	7.45
MGIRE55-10	10.0	9.96	8.23	6.34	5.50	3.96	1.24	8.72
MGIRE55-12	12.0	10.85	8.49	6.25	5.35	3.76	1.01	9.84

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.