

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 40 MHz Reverse Equalizers for:

General Instruments Style Starline Phase II SRE-S/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz					Tilt (dB)
		5	15	25	30	40	
MGISRES-00	0.0	2.27	2.14	1.90	1.72	0.80	1.47
MGISRES-01	1.0	3.28	2.98	2.66	2.41	1.17	2.11
MGISRES-02	2.0	3.45	3.03	2.53	2.22	0.65	2.80
MGISRES-03	3.0	4.26	3.66	3.02	2.66	1.16	3.10
MGISRES-04	4.0	4.91	4.08	3.23	2.75	0.81	4.10
MGISRES-05	5.0	5.44	4.40	3.37	2.81	0.83	4.61
MGISRES-06	6.0	6.05	4.76	3.55	2.91	0.95	5.10
MGISRES-07	7.0	6.95	5.25	3.85	3.15	1.01	5.94
MGISRES-08	8.0	7.65	5.84	4.20	3.31	0.98	6.67
MGISRES-09	9.0	8.32	6.21	4.38	3.43	1.10	7.22
MGISRES-10	10.0	8.95	6.58	4.59	3.66	0.95	8.00
MGISRES-11	11.0	9.72	7.06	4.84	3.77	1.20	8.52
MGISRES-12	12.0	10.31	7.29	4.89	3.72	0.84	9.47
MGISRES-13	13.0	11.02	7.81	5.29	4.02	1.00	10.02
MGISRES-14	14.0	11.68	8.15	5.26	3.86	1.03	10.65
MGISRES-15	15.0	12.22	8.54	5.65	4.25	1.08	11.14
MGISRES-16	16.0	12.90	9.00	5.86	4.33	1.12	11.78

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.