

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p><a href="http://www.main-line-inc.com">www.main-line-inc.com</a> e-mail: <a href="mailto:sales@main-line-inc.com">sales@main-line-inc.com</a> <a href="mailto:engineering@main-line-inc.com">engineering@main-line-inc.com</a></p>
--	------------------------------	--

Replacement 750 MHz Cable Simulators for:

### C-COR Style SCS-750/\* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz								Tilt (dB)
		50	100	200	300	400	500	600	750	
MCCRE-00	<b>0.0</b>	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	<b>0.0</b>
MCCRC750-02	<b>2.0</b>	1.0	1.1	1.3	1.4	1.5	1.6	1.7	1.8	<b>0.8</b>
MCCRC750-03	<b>3.0</b>	1.0	1.2	1.6	1.8	2.1	2.3	2.5	2.8	<b>1.8</b>
MCCRC750-04	<b>4.0</b>	1.0	1.3	1.8	2.2	2.5	2.8	3.1	3.5	<b>2.5</b>
MCCRC750-05	<b>5.0</b>	1.0	1.4	2.2	2.7	3.3	3.7	4.1	4.6	<b>3.6</b>
MCCRC750-06	<b>6.0</b>	1.0	1.6	2.7	3.5	4.2	4.8	5.5	6.2	<b>5.2</b>
MCCRC750-07	<b>7.0</b>	1.0	1.7	2.8	3.8	4.5	5.2	5.9	6.8	<b>5.8</b>
MCCRC750-08	<b>8.0</b>	1.0	1.8	3.2	4.2	5.1	6.0	6.8	7.8	<b>6.8</b>
MCCRC750-09	<b>9.0</b>	1.0	2.0	3.6	4.8	5.9	6.9	7.8	9.0	<b>8.0</b>
MCCRC750-10	<b>10.0</b>	1.0	2.0	3.7	5.1	6.2	7.2	8.3	9.5	<b>8.5</b>
MCCRC750-11	<b>11.0</b>	1.0	2.2	4.1	5.7	7.0	8.1	9.3	10.7	<b>9.7</b>
MCCRC750-12	<b>12.0</b>	1.0	2.3	4.5	6.2	7.6	8.9	10.2	11.8	<b>10.8</b>
MCCRC750-13	<b>13.0</b>	1.0	2.4	4.8	6.6	8.2	9.6	11.0	12.7	<b>11.7</b>
MCCRC750-14	<b>14.0</b>	1.0	2.6	5.2	7.3	9.0	10.6	12.2	14.1	<b>13.1</b>
MCCRC750-15	<b>15.0</b>	1.0	2.7	5.5	7.7	9.6	11.3	13.0	15.0	<b>14.0</b>

Return Loss I/O: **18/16 dB**

Passband Flatness: **0.6 dB**, Peak to Valley

*Note: Measurements on individual cable simulators may differ slightly from these values.*

\*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.