

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 65 MHz Reverse Equalizers for:

C-COR Style MEQ-65/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz						Tilt (dB)
		5	20	33	42	55	65	
MCCRRE-00	0.0	0.00	0.00	0.00	0.00	0.00	0.00	0.00
MCCRRE65-02	2.0	1.82	1.44	1.22	1.08	0.91	0.82	1.00
MCCRRE65-03	3.0	2.95	2.25	1.84	1.58	1.24	0.96	1.99
MCCRRE65-04	4.0	3.86	2.62	2.04	1.73	1.33	0.94	2.92
MCCRRE65-05	5.0	5.09	3.51	2.58	2.05	1.38	0.88	4.21
MCCRRE65-06	6.0	6.09	4.14	3.00	2.28	1.42	0.83	5.26
MCCRRE65-07	7.0	7.02	4.65	3.29	2.46	1.35	0.60	6.42

Return Loss I/O: **18/16 dB**

Passband Flatness: **+/-0.10 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.