

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 65 MHz Reverse Equalizers for:

General Instruments Style SEE-A/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz					Tilt (dB)
		5	30	42	55	65	
MGIRESEEA-02	2.0	3.81	3.03	2.57	1.80	0.55	3.26
MGIRESEEA-04	4.0	5.02	3.49	2.74	1.54	0.30	4.72
MGIRESEEA-06	6.0	6.60	4.25	3.27	1.79	0.36	6.24
MGIRESEEA-08	8.0	8.58	5.45	4.26	2.65	1.06	7.52
MGIRESEEA-10	10.0	9.90	6.02	4.62	2.78	1.05	8.85
MGIRESEEA-12	12.0	11.65	6.94	5.12	2.82	1.00	10.65

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.