

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 30 MHz Reverse Equalizers for:

General Instruments Style SEE-E/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz				Tilt (dB)
		5	15	25	30	
MGIRESEEE-02	2.0	2.94	2.30	1.53	0.79	2.15
MGIRESEEE-04	4.0	4.00	2.85	1.68	0.72	3.28
MGIRESEEE-06	6.0	5.75	4.05	2.49	1.25	4.50
MGIRESEEE-08	8.0	6.89	4.60	2.50	1.13	5.76
MGIRESEEE-10	10.0	8.04	4.94	2.40	1.04	7.00
MGIRESEEE-12	12.0	9.24	5.69	2.93	1.23	8.01

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.25 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.