

	<h2 style="margin: 0;">SPECIFICATION SHEET</h2>	<p style="margin: 0;">20917 Higgins Court Torrance, Ca. 90501</p> <p style="margin: 0;">Phone: 310-357-4450 800-444-2288</p> <p style="margin: 0;">Fax: 310-357-4465</p> <p style="margin: 0;"><a href="http://www.main-line-inc.com">www.main-line-inc.com</a></p> <p style="margin: 0;">e-mail: <a href="mailto:sales@main-line-inc.com">sales@main-line-inc.com</a> <a href="mailto:engineering@main-line-inc.com">engineering@main-line-inc.com</a></p>
--	---	---

### MLE1000 EQ Triple Spec

Part Number	EQ Value @ Stated Frequency	Insertion Loss (dB)
<b>MLE1000-01</b>	1.0 DB @ 1000 MHZ	1.0
	0.9 DB @ 862 MHZ	1.0
	0.8 DB @ 750 MHZ	1.0
<b>MLE1000-02</b>	2.0 DB @ 1000 MHZ	1.0
	1.9 DB @ 862 MHZ	1.0
	1.8 DB @ 750 MHZ	1.0
<b>MLE1000-03</b>	3.0 DB @ 1000 MHZ	1.0
	2.9 DB @ 862 MHZ	1.0
	2.8 DB @ 750 MHZ	1.0
<b>MLE1000-04</b>	4.0 DB @ 1000 MHZ	1.0
	3.9 DB @ 862 MHZ	1.0
	3.8 DB @ 750 MHZ	1.1
<b>MLE1000-05</b>	5.0 DB @ 1000 MHZ	1.0
	4.8 DB @ 862 MHZ	1.0
	4.6 DB @ 750 MHZ	1.2
<b>MLE1000-06</b>	6.0 DB @ 1000 MHZ	1.0
	5.5 DB @ 862 MHZ	1.0
	5.2 DB @ 750 MHZ	1.3
<b>MLE1000-07</b>	7.0 DB @ 1000 MHZ	1.0
	6.6 DB @ 862 MHZ	1.0
	6.3 DB @ 750 MHZ	1.4
<b>MLE1000-08</b>	8.0 DB @ 1000 MHZ	1.0
	7.5 DB @ 862 MHZ	1.0
	7.2 DB @ 750 MHZ	1.4
<b>MLE1000-09</b>	9.0 DB @ 1000 MHZ	1.0
	8.5 DB @ 862 MHZ	1.4
	8.0 DB @ 750 MHZ	2.1
<b>MLE1000-10</b>	10.0 DB @ 1000 MHZ	1.0
	9.2 DB @ 862 MHZ	1.3
	8.8 DB @ 750 MHZ	2.0
<b>MLE1000-11</b>	11.0 DB @ 1000 MHZ	1.0
	10.3 DB @ 862 MHZ	1.3
	9.6 DB @ 750 MHZ	2.1

Part Number	EQ Value @ Stated Frequency	Insertion Loss (dB)
<b>MLE1000-12</b>	12.0 DB @ 1000 MHZ	1.0
	11.2 DB @ 862 MHZ	1.4
	10.6 DB @ 750 MHZ	2.2
<b>MLE1000-13</b>	13.0 DB @ 1000 MHZ	1.0
	12.2 DB @ 862 MHZ	1.6
	11.4 DB @ 750 MHZ	2.5
<b>MLE1000-14</b>	14.0 DB @ 1000 MHZ	1.0
	13.0 DB @ 862 MHZ	1.6
	12.2 DB @ 750 MHZ	2.6
<b>MLE1000-15</b>	15.0 DB @ 1000 MHZ	1.0
	13.9 DB @ 862 MHZ	1.8
	13.0 DB @ 750 MHZ	2.8
<b>MLE1000-16</b>	16.0 DB @ 1000 MHZ	1.0
	14.8 DB @ 862 MHZ	2.4
	13.8 DB @ 750 MHZ	3.4
<b>MLE1000-17</b>	17.0 DB @ 1000 MHZ	1.0
	15.6 DB @ 862 MHZ	2.2
	14.4 DB @ 750 MHZ	3.4
<b>MLE1000-18</b>	18.0 DB @ 1000 MHZ	1.0
	16.6 DB @ 862 MHZ	2.6
	15.6 DB @ 750 MHZ	3.7
<b>MLE1000-19</b>	19.0 DB @ 1000 MHZ	1.0
	17.4 DB @ 862 MHZ	2.6
	16.4 DB @ 750 MHZ	3.7
<b>MLE1000-20</b>	20.0 DB @ 1000 MHZ	1.0
	18.5 DB @ 862 MHZ	2.5
	17.1 DB @ 750 MHZ	3.9
<b>MLE1000-21</b>	21.0 DB @ 1000 MHZ	1.0
	19.6 DB @ 862 MHZ	2.9
	18.4 DB @ 750 MHZ	4.3

\*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.