

	<h1>SPECIFICATION SHEET</h1>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 1000 MHz Attenuators (Pads) for:

C-COR Style IPB/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz							Attenuation (dB)
		5	350	450	550	750	860	1000	
MMGIP-00	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
MMGIP-01	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
MMGIP-02	2.0	2.0	2.0	2.0	2.0	2.0	2.0	2.0	2.0
MMGIP-03	3.0	3.0	3.0	3.0	3.0	3.0	3.0	3.0	3.0
MMGIP-04	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0
MMGIP-05	5.0	5.0	5.0	5.0	5.0	5.0	5.0	5.0	5.0
MMGIP-06	6.0	6.0	6.0	6.0	6.0	6.0	6.0	6.0	6.0
MMGIP-07	7.0	7.0	7.0	7.0	7.0	7.0	7.0	7.0	7.0
MMGIP-08	8.0	8.0	8.0	8.0	8.0	8.0	8.0	8.0	8.0
MMGIP-09	9.0	9.0	9.0	9.0	9.0	9.0	9.0	9.0	9.0
MMGIP-10	10.0	10.0	10.0	10.0	10.0	10.0	10.0	10.0	10.0
MMGIP-11	11.0	11.0	11.0	11.0	11.0	11.0	11.0	11.0	11.0
MMGIP-12	12.0	12.0	12.0	12.0	12.0	12.0	12.0	12.0	12.0
MMGIP-13	13.0	13.0	13.0	13.0	13.0	13.0	13.0	13.0	13.0
MMGIP-14	14.0	14.0	14.0	14.0	14.0	14.0	14.0	14.0	14.0
MMGIP-15	15.0	15.0	15.0	15.0	15.0	15.0	15.0	15.0	15.0
MMGIP-16	16.0	16.0	16.0	16.0	16.0	16.0	16.0	16.0	16.0
MMGIP-17	17.0	17.0	17.0	17.0	17.0	17.0	17.0	17.0	17.0
MMGIP-18	18.0	18.0	18.0	18.0	18.0	18.0	18.0	18.0	18.0
MMGIP-19	19.0	19.0	19.0	19.0	19.0	19.0	19.0	19.0	19.0
MMGIP-20	20.0	20.0	20.0	20.0	20.0	20.0	20.0	20.0	20.0

Return Loss I/O: **19/19 dB**

Passband Flatness: **+/-0.30 dB** (-01 through -05)
+/-0.50 dB (-06 through -08)
+/-0.70 dB (-09 through -11)
+/-1.0 dB (-12 through -20)

Note: Measurements on individual attenuators (pads) may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.