

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p><a href="http://www.main-line-inc.com">www.main-line-inc.com</a> e-mail: <a href="mailto:sales@main-line-inc.com">sales@main-line-inc.com</a> <a href="mailto:engineering@main-line-inc.com">engineering@main-line-inc.com</a></p>
--	------------------------------	--

Replacement 1200 MHz Attenuators (Pads) for:

### General Instruments Style JXP/\* (1" Handle) Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz							Attenuation (dB)	Tilt (dB)
		5	350	450	550	750	870	1200		
MMGIP-00	<b>0.0</b>	0.0	0.0	0.0	0.0	0.0	0.0	0.0	<b>0.0</b>	+/-0.10
MMGIP-01	<b>1.0</b>	1.0	1.0	1.0	1.0	1.0	1.0	1.0	<b>1.0</b>	+/-0.10
MMGIP-02	<b>2.0</b>	2.0	2.0	2.0	2.0	2.0	2.0	2.0	<b>2.0</b>	+/-0.10
MMGIP-03	<b>3.0</b>	3.0	3.0	3.0	3.0	3.0	3.0	3.0	<b>3.0</b>	+/-0.10
MMGIP-04	<b>4.0</b>	4.0	4.0	4.0	4.0	4.0	4.0	4.0	<b>4.0</b>	+/-0.10
MMGIP-05	<b>5.0</b>	5.0	5.0	5.0	5.0	5.0	5.0	5.0	<b>5.0</b>	+/-0.15
MMGIP-06	<b>6.0</b>	6.0	6.0	6.0	6.0	6.0	6.0	6.0	<b>6.0</b>	+/-0.15
MMGIP-07	<b>7.0</b>	7.0	7.0	7.0	7.0	7.0	7.0	7.0	<b>7.0</b>	+/-0.15
MMGIP-08	<b>8.0</b>	8.0	8.0	8.0	8.0	8.0	8.0	8.0	<b>8.0</b>	+/-0.15
MMGIP-09	<b>9.0</b>	9.0	9.0	9.0	9.0	9.0	9.0	9.0	<b>9.0</b>	+/-0.15
MMGIP-10	<b>10.0</b>	10.0	10.0	10.0	10.0	10.0	10.0	10.0	<b>10.0</b>	+/-0.10
MMGIP-11	<b>11.0</b>	11.0	11.0	11.0	11.0	11.0	11.0	11.0	<b>11.0</b>	+/-0.10
MMGIP-12	<b>12.0</b>	12.0	12.0	12.0	12.0	12.0	12.0	12.0	<b>12.0</b>	+/-0.10
MMGIP-13	<b>13.0</b>	13.0	13.0	13.0	13.0	13.0	13.0	13.0	<b>13.0</b>	+/-0.15
MMGIP-14	<b>14.0</b>	14.0	14.0	14.0	14.0	14.0	14.0	14.0	<b>14.0</b>	+/-0.20
MMGIP-15	<b>15.0</b>	15.0	15.0	15.0	15.0	15.0	15.0	15.0	<b>15.0</b>	+/-0.25
MMGIP-16	<b>16.0</b>	16.0	16.0	16.0	16.0	16.0	16.0	16.0	<b>16.0</b>	+/-0.25
MMGIP-17	<b>17.0</b>	17.0	17.0	17.0	17.0	17.0	17.0	17.0	<b>17.0</b>	+/-0.25
MMGIP-18	<b>18.0</b>	18.0	18.0	18.0	18.0	18.0	18.0	18.0	<b>18.0</b>	+/-0.25
MMGIP-19	<b>19.0</b>	19.0	19.0	19.0	19.0	19.0	19.0	19.0	<b>19.0</b>	+/-0.25
MMGIP-20	<b>20.0</b>	20.0	20.0	20.0	20.0	20.0	20.0	20.0	<b>20.0</b>	+/-0.35
MMGIP-75	<b>75 ohm</b>	N/A	N/A	N/A	N/A	N/A	N/A	N/A	<b>N/A</b>	N/A

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.15 dB**

*Note: Measurements on individual attenuators (pads) may differ slightly from these values.*

\*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.