

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 1200 MHz Attenuators (Pads) for:

General Instruments Style Starline Phase II JXP/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz							Attenuation (dB)	Tilt (dB)
		5	350	450	550	750	870	1200		
MMGIP2-00	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	+/-0.10
MMGIP2-01	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	+/-0.10
MMGIP2-02	2.0	2.0	2.0	2.0	2.0	2.0	2.0	2.0	2.0	+/-0.10
MMGIP2-03	3.0	3.0	3.0	3.0	3.0	3.0	3.0	3.0	3.0	+/-0.10
MMGIP2-04	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	+/-0.10
MMGIP2-05	5.0	5.0	5.0	5.0	5.0	5.0	5.0	5.0	5.0	+/-0.15
MMGIP2-06	6.0	6.0	6.0	6.0	6.0	6.0	6.0	6.0	6.0	+/-0.15
MMGIP2-07	7.0	7.0	7.0	7.0	7.0	7.0	7.0	7.0	7.0	+/-0.15
MMGIP2-08	8.0	8.0	8.0	8.0	8.0	8.0	8.0	8.0	8.0	+/-0.15
MMGIP2-09	9.0	9.0	9.0	9.0	9.0	9.0	9.0	9.0	9.0	+/-0.15
MMGIP2-10	10.0	10.0	10.0	10.0	10.0	10.0	10.0	10.0	10.0	+/-0.10
MMGIP2-11	11.0	11.0	11.0	11.0	11.0	11.0	11.0	11.0	11.0	+/-0.10
MMGIP2-12	12.0	12.0	12.0	12.0	12.0	12.0	12.0	12.0	12.0	+/-0.10
MMGIP2-13	13.0	13.0	13.0	13.0	13.0	13.0	13.0	13.0	13.0	+/-0.15
MMGIP2-14	14.0	14.0	14.0	14.0	14.0	14.0	14.0	14.0	14.0	+/-0.20
MMGIP2-15	15.0	15.0	15.0	15.0	15.0	15.0	15.0	15.0	15.0	+/-0.25
MMGIP2-16	16.0	16.0	16.0	16.0	16.0	16.0	16.0	16.0	16.0	+/-0.25
MMGIP2-17	17.0	17.0	17.0	17.0	17.0	17.0	17.0	17.0	17.0	+/-0.25
MMGIP2-18	18.0	18.0	18.0	18.0	18.0	18.0	18.0	18.0	18.0	+/-0.25
MMGIP2-19	19.0	19.0	19.0	19.0	19.0	19.0	19.0	19.0	19.0	+/-0.25
MMGIP2-20	20.0	20.0	20.0	20.0	20.0	20.0	20.0	20.0	20.0	+/-0.35
MMGIP2-75	75 ohm	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.15 dB**

Note: Measurements on individual attenuators (pads) may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.