

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 330 MHz Forward Equalizers for:

Scientific Atlanta Style EQ330/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz				Tilt (dB)
		46	150	250	330	
MSAE-00	0.0	0.00	0.00	0.00	0.00	0.00
MSAE330-1.5	1.5	1.46	0.52	0.39	0.20	1.26
MSAE330-03	3.0	2.06	1.12	0.59	0.22	1.84
MSAE330-4.5	4.5	2.83	1.80	0.81	0.25	2.58
MSAE330-06	6.0	4.20	2.47	1.12	0.39	3.81
MSAE330-7.5	7.5	5.28	3.12	1.62	0.48	4.80
MSAE330-09	9.0	6.39	3.77	1.91	0.51	5.88
MSAE330-10.5	10.5	6.94	3.88	1.67	0.22	6.72
MSAE330-12	12.0	8.11	4.59	2.10	0.31	7.80
MSAE330-13.5	13.5	9.21	5.22	2.47	0.50	8.71
MSAE330-15	15.0	10.17	5.90	2.93	0.70	9.47
MSAE330-16.5	16.5	11.06	6.27	3.00	0.76	10.30
MSAE330-18	18.0	11.91	6.80	3.06	0.54	11.37
MSAE330-19.5	19.5	13.32	7.87	3.73	1.02	12.30
MSAE330-21	21.0	13.88	8.11	3.56	0.66	13.22
MSAE330-22.5	22.5	14.59	8.33	3.53	0.63	13.96
MSAE330-24	24.0	15.74	8.93	3.93	0.66	15.08
MSAE330-25.5	25.5	16.76	9.48	4.20	0.57	16.19
MSAE330-27	27.0	17.77	10.30	4.64	0.83	16.94
MSAE330-28.5	28.5	18.97	11.00	5.05	1.02	17.95
MSAE330-30	30.0	20.22	11.72	5.55	1.25	18.97

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.15 dB** cable equivalent

Note: Measurements on individual forward equalizers may differ slightly from these values.

*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, C-Cor, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.