

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 1002 MHz Signal Directors for:

Scientific Atlanta GainMaker Style 1002 MHz Series Manufactured By Mainline

Part Number	Type	Path	Insertion Loss (dB) @ MHz						
			52	550	600	650	750	870	1002
MSAGM589281	Jumper	----	0.10	0.20	0.20	0.20	0.20	0.20	0.30
MSAGM589357	Splitter	----	3.39	3.38	3.35	3.41	3.43	3.67	4.20
MSAGM589363	DC-8	Thru	1.45	1.55	1.52	1.62	1.67	1.96	2.31
		Tap	8.30	7.89	7.76	7.85	7.71	7.72	8.00
MSAGM589367	DC-12	Thru	0.95	0.64	0.63	0.67	0.71	0.98	1.25
		Tap	12.67	11.99	11.81	11.92	11.70	11.66	11.94

Return Loss I/O: **18/18 dB**

Note: Measurements on individual signal directors may differ slightly from these values.