

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement Reverse Equalizers for:

Scientific Atlanta Gain Maker Style 40/ 42 MHz Series Manufactured By Mainline

Part Number	Value @ 40 MHz (dB)	Value @ 42 MHz (dB)	Insertion Loss @ MHz			Tilt (dB)
			5	40	42	
MSAGMRE-00	0.0	0.0	0.0	0.0	0.0	0.0
MSAGMRE40-01	1.0	1.0	1.7	1.0	1.0	0.7
MSAGMRE40-02	2.0	2.0	2.3	1.0	1.0	1.3
MSAGMRE40-03	3.0	3.1	3.0	1.0	0.9	2.0
MSAGMRE40-04	4.0	4.1	3.6	1.0	0.9	2.6
MSAGMRE40-05	5.0	5.1	4.3	1.0	0.9	3.3
MSAGMRE40-06	6.0	6.1	4.9	1.0	0.9	3.9
MSAGMRE40-07	7.0	7.2	5.6	1.0	0.8	4.6
MSAGMRE40-08	8.0	8.2	6.2	1.0	0.8	5.2
MSAGMRE40-09	9.0	9.2	6.9	1.0	0.8	5.9
MSAGMRE40-10	10.0	10.2	7.5	1.0	0.8	6.5
MSAGMRE40-11	11.0	11.3	8.0	1.0	0.7	7.0
MSAGMRE40-12	12.0	12.3	8.9	1.0	0.7	7.9

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.20 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.