

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement Reverse Equalizers for:

Scientific Atlanta Gain Maker Style 55 MHz Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz				Tilt (dB)
		5	30	40	55	
MSAGMRE-00	0.0	0.00	0.00	0.00	0.00	0.00
MSAGMRE55-01	1.0	1.12	0.74	0.60	0.42	0.70
MSAGMRE55-02	2.0	1.88	1.08	0.82	0.48	1.40
MSAGMRE55-03	3.0	2.46	1.21	0.85	0.36	2.10
MSAGMRE55-04	4.0	3.08	1.38	0.88	0.28	2.80
MSAGMRE55-05	5.0	4.19	2.02	1.45	0.69	3.50
MSAGMRE55-06	6.0	4.89	2.26	1.58	0.69	4.20
MSAGMRE55-07	7.0	5.46	2.34	1.55	0.56	4.90
MSAGMRE55-08	8.0	6.22	2.67	1.70	0.52	5.70
MSAGMRE55-09	9.0	6.90	2.93	1.79	0.50	6.40
MSAGMRE55-10	10.0	7.56	3.13	1.91	0.46	7.10
MSAGMRE55-11	11.0	8.06	3.19	1.82	0.26	7.80
MSAGMRE55-12	12.0	9.14	3.83	2.40	0.64	8.50

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/-0.20 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.