

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p><a href="http://www.main-line-inc.com">www.main-line-inc.com</a> e-mail: <a href="mailto:sales@main-line-inc.com">sales@main-line-inc.com</a> <a href="mailto:engineering@main-line-inc.com">engineering@main-line-inc.com</a></p>
--	------------------------------	--

Replacement Reverse Equalizers for:

### Scientific Atlanta Gain Maker Style 65 MHz Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz		Tilt (dB)
		5	65	
MSAGMRE-00	<b>0.0</b>	0.0	0.0	<b>0.0</b>
MSAGMRE65-01	<b>1.0</b>	1.7	1.0	<b>0.7</b>
MSAGMRE65-02	<b>2.0</b>	2.5	1.0	<b>1.5</b>
MSAGMRE65-03	<b>3.0</b>	3.2	1.0	<b>2.2</b>
MSAGMRE65-04	<b>4.0</b>	3.9	1.0	<b>2.9</b>
MSAGMRE65-05	<b>5.0</b>	4.7	1.0	<b>3.7</b>
MSAGMRE65-06	<b>6.0</b>	5.4	1.0	<b>4.4</b>
MSAGMRE65-07	<b>7.0</b>	6.1	1.0	<b>5.1</b>
MSAGMRE65-08	<b>8.0</b>	6.9	1.0	<b>5.9</b>
MSAGMRE65-09	<b>9.0</b>	7.6	1.0	<b>6.6</b>
MSAGMRE65-10	<b>10.0</b>	8.3	1.0	<b>7.3</b>
MSAGMRE65-11	<b>11.0</b>	9.0	1.0	<b>8.0</b>
MSAGMRE65-12	<b>12.0</b>	9.8	1.0	<b>8.8</b>

Return Loss I/O: **18/18 dB**

Passband Flatness: **+/- 0.20 dB** cable equivalent

*Note: Measurements on individual reverse equalizers may differ slightly from these values.*