

	<h2>SPECIFICATION SHEET</h2>	<p>20917 Higgins Court Torrance, Ca. 90501</p> <p>Phone: 310-357-4450 800-444-2288 Fax: 310-357-4465</p> <p>www.main-line-inc.com e-mail: sales@main-line-inc.com engineering@main-line-inc.com</p>
--	------------------------------	--

Replacement 65 MHz Reverse Equalizers for:

Scientific Atlanta Style EQ65T/* Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz								Tilt (dB)
		5	10	15	25	35	45	55	65	
MSARE-00	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
MSARE65T-1.5	1.5	2.1	1.9	1.8	1.6	1.4	1.3	1.1	1.0	1.1
MSARE65T-03	3.0	3.2	2.9	2.6	2.2	1.8	1.5	1.3	1.0	2.2
MSARE65T-4.5	4.5	4.3	3.8	3.4	2.8	2.2	1.8	1.4	1.0	3.3
MSARE65T-06	6.0	5.4	4.7	4.2	3.3	2.7	2.0	1.5	1.0	4.4
MSARE65T-7.5	7.5	6.5	5.6	5.0	3.9	3.1	2.3	1.6	1.0	5.5
MSARE65T-09	9.0	7.6	6.6	5.8	4.5	3.5	2.6	1.8	1.0	6.6
MSARE65T-10.5	10.5	8.7	7.5	6.6	5.1	3.9	2.8	1.9	1.0	7.7
MSARE65T-12	12.0	9.8	8.4	7.4	5.7	4.3	3.1	2.0	1.0	8.8

Return Loss I/O: **18/18 dB.**

Passband Flatness: **+/-0.20 dB** cable equivalent

Note: Measurements on individual reverse equalizers may differ slightly from these values.