



# SPECIFICATION SHEET

20917 Higgins Court  
Torrance, Ca. 90501

Phone: 310-357-4450  
800-444-2288

Fax: 310-357-4465

[www.main-line-inc.com](http://www.main-line-inc.com)

e-mail: [sales@main-line-inc.com](mailto:sales@main-line-inc.com)  
[engineering@main-line-inc.com](mailto:engineering@main-line-inc.com)

Replacement Forward Equalizers for:

## Texscan Style 550 MHz Series Manufactured By Mainline

Part Number	Value (dB)	Insertion Loss @ MHz						Total Tilt (dB)
		50	150	250	350	450	550	
<b>MTEXE550-08</b>	8.0	6.30	4.45	2.86	1.75	0.91	0.22	<b>6.08</b>
<b>MTEXE550-10</b>	10.0	7.80	5.55	3.84	2.49	1.40	0.32	<b>7.48</b>
<b>MTEXE550-12</b>	12.0	9.11	6.84	4.54	2.78	1.47	0.28	<b>8.83</b>
<b>MTEXE550-14</b>	14.0	10.87	7.38	4.64	2.79	1.48	0.30	<b>10.57</b>
<b>MTEXE550-16</b>	16.0	11.92	8.83	6.06	3.69	1.77	0.31	<b>11.61</b>
<b>MTEXE550-18</b>	18.0	13.44	9.54	6.09	3.47	1.48	0.15	<b>13.29</b>
<b>MTEXE550-20</b>	20.0	15.76	11.45	7.84	4.94	2.60	0.86	<b>14.90</b>

Return Loss I/O: **18/18 dB**.

Passband Flatness: +/- **0.15 dB** cable equivalent.

*Note: Measurements on individual equalizers may differ slightly from these values.*

\*Main Line Equipment Inc. is a manufacturer of equivalent replacement Equalizers, Pads and Plug-ins. Main Line Equipment Inc. is not a sales agent for Augat, Motorola (GI), Scientific Atlanta, Antec (Texscan) or Alpha Power Supply.